

HPA 100 / 110 / 120 AC / HPA 130 DC

Powerful High-Voltage test system

up to 100 / 110 / 120 kV_{RMS} AC / 130 kV DC

Megger[®]



- Continuous testing with AC voltages up to 100 kV_{RMS} at 5 kVA
- Suitable for sensitive PD measurements
- Built-in overcurrent protection
- DC testing up to 130 kV with optional rectifier

DESCRIPTION

The AC Test Set HPA 100 is a powerful test set. The unit has been designed to test low to medium types of capacitive objects such as transformers, switchgears, isolated bus-bars and bushings.

The test set can be equipped with a rectifier attachment for DC testing up to 130 kV. Since the system's own noise level is below 1pC, it is also suitable as a voltage source for PD measurements.

The two piece design allows the operator to use the unit at a safe distance. The control unit is used for controlling the high voltage transformer. The unit consists of a variac, current/ voltage display instruments, a timer for the test duration and a safety circuit.

The low voltage winding can be continuously excited from zero to the maximum value so that a certain output is available for a pre-determined period. The operating duration depends on the application, ranging from a few minutes to continuous operation. The test transformer is single-pole insulated and mounted in an insulated cylinder with top and bottom flanges. The insulation material is primarily oil impregnated paper.

HPA 100 / 110 / 120 AC / HPA 130 DC

Powerful High-Voltage test system

up to 100 / 110 / 120 kV_{RMS} AC / 130 kV DC

TECHNICAL DATA*

Power consumption P_n	5 kVA
Power consumption short-time P_k (1h)	7.5 kVA
Input voltage	230 V/50 ... 60 Hz
Output voltage	0 ... 100 kV _{RMS} AC (HPA 100) 0 ... 110 kV _{RMS} AC (HPA 110) 0 ... 120 kV _{RMS} AC (HPA 120) 0 ... 130 kV DC'
Measuring range	0 ... 100 kV _{RMS} AC 0 ... 150 kV DC
Precision	2.5 %
Output current	0 ... 50 mA _{RMS} continuous, 75 mA _{RMS} short circuit current (1 h)
Measuring range	0 ... 1/0 ... 10/0 ... 100 mA _{RMS} AC 0 ... 0.1/0 ... 1/0 ... 10/0 ... 100 mA DC
PD at rated voltage	< 1 pC
Steuergerät HSG 10-1	
Weight	75 kg / 165 lbs.
Dimensions	520 x 430 x 465 mm 20.5 in. x 16.9 in. x 18.3 in.
Transformator HTR 100	
Weight	225 kg / 496 lbs.
Dimensions	540 x 785 x 540 mm 20.5 in. x 30.9 in. x 21.3 in.

FEATURES

- High power AC test set
 - Ideal for testing of HV-components such as switchgear, bus-bars etc.
 - Suitable for sensitive PD measurements
 - Two piece design
- #### SCOPE OF DELIVERY
- Control unit HSG 10-1
 - Transformer HTR 100
 - Set of cables HPA 100, 5 m
 - Earthing stick 150 kV

ORDERING INFORMATION

Product	Order no.
HPA 100 (AC 100 kV _{RMS} only)	820004061
HPA 110 (AC 110 kV _{RMS} only)	1004466
HPA 120 (AC 120 kV _{RMS} only)	1005226
HPA 130 (AC 100 kV _{RMS} / DC 130 kV)	813208
Options:	
HV connection cable 3 m (unshielded)	2013483
HV connection cable 5 m (unshielded)	2013484
HV connection cable 10 m (unshielded)	2013485

* We reserve the right to make technical changes.

SALES OFFICE

Megger Germany GmbH
Dr.-Herbert-lann-Str. 6
96148 Baunach
Germany
T +49 9544 68-0
E team.international@megger.com

HPA100AC_DS_EN_V03

www.megger.com
ISO 9001
The word 'Megger' is a registered trademark.

Megger[®]